



100A Brushless Smart ESC Programmable Options

Programmable Items	Parameter Options						
	1	2	3	4	5	6	7
1. Battery Type	LiPo	NiMH					
2. Punch	Level 1	Level 2	Level 3	Level 4	Level 5		
3. Brake Force	25%	37.50%	50%	62.50%	75%	87.50%	100%
4. Running Mode	Forward/Reverse w/ Brake	Forward w/ Brake					
5. Motor Rotation	CCW	CW					
6. BEC	6.0V	7.4V					

* The blacked out cells with white text are the default settings.

©2020 Horizon Hobby, LLC. Firma and the Firma logo are trademarks of Horizon Hobby, LLC. The Spektrum trademark is used with permission of Bachmann Industries, Inc.



64691 Firma 100 Amp Smart Brushless ESC SPMXSE1100



100A Brushless Smart ESC Specifications

SPMXSE1100

Continuous Current	100A
Burst Current	650A
Input Voltage	2 - 3S LiPo / 5 - 9S NiMH
BEC Output	6V/7.4V @ 4A
Size / Weight	43 x 39 (54.5 @ tabs) x 33.3 mm / 139g

Battery Connector(s)	IC5 (EC5 Compatible)
Motor Connector	4mm Female Bullet
Motor Type	Sensorless Brushless
Waterproof	IP67 Rated
Telemetry	SRXL2 Compatible Spektrum Smart Technology

